



## DGH 9000 P

Portable Professional Range



POWER (PRP):  
8 kVA / 8 kW

FREQUENCY  
50Hz

VOLTAGE  
230V

WEIGHT WITHOUT WHEELS:  
100kg

DIMENSIONS WITHOUT WHEELS:  
L: 820 mm  
W: 560 mm  
H: 532 mm

Image for orientation purposes. Transport kit not included in the standard scope of delivery. Dagartech reserves the right to modify the data in this technical sheet without prior notice.

Unleaded gasoline

EU Stage V

Air-cooled

Static frame

CE certified

## 1. General technical data

### General technical data

Engine	HONDA GX390	
Alternator	LINZ E1C11M B	
Frequency	50Hz	
Voltage	230V	
Work regime (rpm)	3000	
Type of regulation	centrifugal mass	
Power factor ( $\cos \varphi$ )	1	
Tank (l)	15	
Type of start-up	Manual	

### Powers<sup>1</sup> (p.f. $\cos \varphi$ 1)

**PRP (kVA / kW)** **8 / 8**

The transport kit is an option not included in the standard scope of supply of this equipment.

<sup>1</sup>PRP: Prime Power according to ISO8528-1.

### Directives and Regulations

#### ENVIRONMENTAL CONDITIONS STANDARD ISO 8528-1:2018: 25°C, 100kPa and 30% relative humidity:

- **Prime Power (PRP):** Data on electrical power available at variable load without limit of hours per year. An overload of 10% is allowed for 1h out of 12. According to ISO 8528-1:2018.
- **Emergency Standby Power (ESP):** Data on electrical capacity available at variable load in case of emergency according to ISO 8528-1:2018.

#### The DAGARTECH Generator bears the CE marking which includes the following directives:

- **2006/42/EC.** Machine Safety Directive.
- **EN ISO 8528-13:2016.** Part 13: Safety. Alternating current generators powered by reciprocating internal combustion engines.
- **2014/30/EU.** Electromagnetic Compatibility Directive.
- **2000/14/EC.** Noise Emissions Directive. Sound power levels evaluated in accordance with the procedure laid down in the directive.
- **Directive 2011/65/EU** on the restriction of the use of certain hazardous substances in electrical and electronic equipment (RoHS<sup>2</sup>).

230V · 50Hz (3000 rpm)

HONDA GX390 | LINZ E1C11M B

**2.1.**  
**General technical data of the engine**

Make and model	HONDA GX390
r.p.m.	3000
Continuous power - 3,000 rpm (kW/m)	N/A
Max. net power - 3600 rpm (kW/m)	8,7*
Type of regulation	centrifugal mass
Fuel	Unleaded gasoline
No. of cylinders	1
Cylinder capacity (c.c.)	389
Compression ratio	8,2:1
Maximum torque (Nm)	26,4 (2500 r.p.m.)
Cooling system	Air-cooled
Start-up Method	Manual


 4-STROKE-STROKES  
 PETROL ENGINE. AIR-COOLED.


\* Gross power data for VANGUARD and BRIGGS-STRATTON engines.

**2.2. Fuel**

Type of fuel	Unleaded gasoline
Tank capacity	15

**2.3. Consumption and autonomy**

	Consumption (l/h)		Autonomy (h)	
	PRP	ESP	PRP	ESP
75%	1,8	-	8,3	-
100%	2,4	-	6,3	-

**2.4. Lubrication system**

Oil capacity (l)	1,16
Oil consumption (L/H)	N/A

**3. Alternator specifications**
**3.1. General technical data of the alternator**

Make and model	LINZ E1C11M B
No. of poles	2
Insulation class	H
Mechanical protection index	IP23
Voltage regulator	Compound
Power PRP 40°C (kVA)	10
No. of phases	1
Power factor ( $\cos \varphi$ )	1


**Standard regulations that the alternator meets:**

Directives: 2006/42, 2006/95, 2004/108 and amendments thereto.

Complies with: EN 60034-1, CEI 2-3, IEC34-1, VDE 0530, BS 4999-5000, N.F. 5111.

**2-pole**
**alternator, Compound.**

No maintenance required.

**Winding protection** by impregnation with tropicalised epoxy resin.

230V · 50Hz (3000 rpm)

HONDA GX390 | LINZ E1C11M B

## 5. Standard scope of supply for the Professional range and available options

### STANDARD SCOPE OF DELIVERY

HONDA GX390 Manual starter engine	<input checked="" type="checkbox"/>
Alternator LINZ E1C11M B · Compound	<input checked="" type="checkbox"/>
Fuel tank of 15 litres capacity	<input checked="" type="checkbox"/>
-30 dB(A) exhaust silencer	<input checked="" type="checkbox"/>
Compact electro-welded steel frame with anti-vibration dampers	<input checked="" type="checkbox"/>
Top protective metal plate	<input checked="" type="checkbox"/>
Supply without engine lubrication oil	<input checked="" type="checkbox"/>
Engine oil protection	<input checked="" type="checkbox"/>
Fuel stopcock	<input checked="" type="checkbox"/>
Alternator thermal protection	<input checked="" type="checkbox"/>

### Available options

#### Kit 1. Transport

*Includes solid puncture-proof wheels, handles, and stand.*

	WEIGHT WITH WHEELS: 105,5kg
	DIMENSIONS WITH WHEELS: L: 863 mm W: 696 mm H: 661 mm

#### Kit 2. Alternator with AVR

*Check the availability of this option based on the model.*

#### Kit 3. Electric start

*Includes 12V battery. Check availability of this option based on the model.*

### ALTERNATOR POWER SOCKETS CONFIGURATION

	IP44	CEE IP44	CEE IP44	CEE IP44
	Schuko	2P + T 32A	3P + N + T 16A	3P + N + T 32A
<b>DGH 8000 P</b>	1	1	-	-
<b>DGH 9000 P</b>	1	1	-	-
<b>DGH 12000 P</b>	1	1	-	-
<b>DGH 8 TFP</b>	1	-	1	-
<b>DGH 9 TFP</b>	1	-	1	-
<b>DGH 12 TFP</b>	1	-	-	1
<b>DGH 15 TFP</b>	1	-	-	1

Caption

 Included

 Optional

 Not available

 Consult



---

[info@dagartech.com](mailto:info@dagartech.com)

T +34 976 141 655

---



**CUSTOM  
ENERGY  
SOLUTIONS**

[dagartech.com](http://dagartech.com)